

# aragon



The 8008 is the 2-channel amplifier in the Aragon family. This amplifier provides the foundation for a superior 2-channel listening system or an exceptional front or surround-channel amplifier in an ultimate performance immersive home cinema.

## 8008

### 200W dual monoblock amplifier

- modern example of the classic 8000-series performance and ruggedness
- contemporary version of the “classic Aragon V” chassis design
- high-power, high-performance 2-channel amplification
- dual, symmetrical power supply
- ethernet-based control and status monitoring
- readily interfaces with popular home control solutions
- software upgradable
- solid American engineering and construction



power output	200W into 8Ω	400W into 4Ω
THD	<0.015%, both channels driven	<0.03%, both channels driven
frequency response	5Hz to 20kHz +0/-0.1dB	5Hz to 100kHz +0/-1.2dB
tim/dim distortion	0.003%	
s/n	110 dB, A-weighted	
damping factor	400, 8Ω @50Hz	
input sensitivity	1W: 120mV (SE & balanced)	200W: 1.7V (SE & balanced)
input impedance	46kΩ (SE)	70kΩ (bal)
ethernet/RS-232	status & control of standby/on, channel configuration	
12 volt	standby/on control	
inputs	gold-plated, panel-mounted RCA jacks	XLR balanced jack
power consumption	standby: <1W	idle: 120W
outputs	max: 1500W	
physical	2 sets gold-plated, 60-Amp insulated speaker binding posts	
colors	7”(17.8 cm) x 16”(40.6 cm) x 19”(48.3 cm)	63 lbs (28.6 kg)
shipping carton	black or silver w/ satin anodized finish	laser-etched logo
	12”(30.5 cm) x 22”(55.9 cm) x 24”(61 cm)	71 lbs (32.2 kg)